Basis for the selection of the equipment

Zoning

lassification of potentially explosion hazardous areas										
Duration– for information only:	Continuous h	Continuous hazard			Occasional hazard			Temporary hazard		
**** IEC * CENELEC **** Europe	Zone 0 (gas)	Zone 20 (dust)	Zone 20 (lint)	Zone 1 (gas)	Zone 21 (dust)	Zone 21 (lint)	Zone 2 (gas)	Zone 22 (dust)	Zone 22 (lint)	
Equipment protection level (EPL)	Ga	Da	Da	Gb	Db	Db	Gc	Dc	Dc	
*	Class I	Class II	Class III	Class I	Class II	Class III	Class I	Class II	Class III	
North America		Division 1 (gas and dust)				C	Division 2 (gas and dust)			

 \bigcirc

 \square

Equipment categories

Gas	Gas								
Zone	Symbol	Category	Protection requirements						
0		1 G required	2 independant means of protection						
1		2 G required, 1 G possible	1 independant mean of protection						
2		3 G required, 1 G, 2 G possible	normal operation						

Equipment categories Dust-Ex area (ATEX) Dust Zone Symbol Category Protection requirements Zone 20 2 independant means of 20 1 D required \mathbf{A} protection 2 D required, 1 independant mean of 21 \bigcirc 1 D possible protection 22 3 D required, normal operation

Dust groups Dust-Ex area Dust groups Categorie Materials IIIA flammable lints IIIB non conductive dust IIIC conductive dust

Industrial Automation

TURCK



IEC resp. EN 60079-...

Technical marking

Marking of an intrinsically safe apparatus (for example):									
Ex	ia	IIC	T6	Ga					
conform to Euro- pean standard	type of protection (two independent means of protec- tion)	explosion group	temperatur class	equipment protection level					

Marking of an associated apparatus (for example):									
[Ex	ia	Ga]	IIC				
associated apparatus	conform to European standard	type of protection	equipment protection level (EPL)	associated apparatus	Explosion group				

ATEX Directive

1 D, 2 D possible

Legal marking



Marking of an intrinsically safe apparatus acc. to ATEX (for example):										
(Ex)	II	1	G							
symbol	all areas except mining (mining = l)	very high safety level suited for zone 0 (two independent means of protection)	explosion protected agains gas, vapour and mist (D = dusts)							

Additionally, the year of production and the constructional level of safety must be contained in the

Proof of intrinsic safety

According to EN 60079-14 a proof of intrinsic safety must be provided to confirm that the equipment which is interconnected within an assembly accords to the requirements of intrinsic safety. In this context there is a clear distinction between two basically different circuits:

- 1. a simple intrinsically safe circuit with a single associated apparatus and at
- least one intrinsically safe apparatus without additional supply
- 2. more than one associated apparatus which is capable of supplying electrical
- energy to the intrinsically safe circuit, not only during normal service but also in a fault condition.

Simple circuit

The first definition of a simple intrinsically safe circuit requires to observe all electrical limit values stated in the EC type examination certificate and the power characteristics. If these conditions are met, the user is entitled to keep a proof of intrinsic safety. Inductances and capacitances of the installed cables must be taken into account.

Intrinsic safety of a simple circuit is given, if the following conditions are met (application of the 50 % rule for accumulated reactances):

Associated ap- paratus	Condition	intrinsically safe equip- ment + cable
U ₀	≤	UI
I0	≤	lı
P ₀	≤	Pl
LO	2	LI + LC
C ₀	2	CI + CC

ATEX directive EC type examination certificate

L	Marking of the EC type examination certificate acc. to ATEX:								
	ΡΤΒ	13	ATEX	2013	X				
	authorised body	year of issue	acc. to 2014/34/EU	serial certificate number	special conditions				

Complete marking (for example)

Legal and technical marking

In summary, an intrinsically safe equipment for use in Zone 0 has the following complete marking:



*) On equipment for use in dust explosion hazardous areas here the maximum surface temperature e.g. T140° is specified.

In summary, an intrinsically safe equipment for use in Zone 0 has the following complete marking:									
II	(1)	G	[Ex	ia	Ga]	lic			
or also for the dust explosion hazardous area:									
II	(1)	D	[Ex	ia	Da]	IIIC			

Mar	king	of a as	sociate	d appara	tus for ap	plication	in zone 2:			
	3	G	Ex	nA	nC	[ic	Gc]	IIC/IIB	T4	Gc

Overview of ignition protection classes

Symbol	Name	Standard	Comments	Zone
(Ex)	General requirements	EN 60079-0	EN 60079-0 comprises general regulations on the construction and testing of electrical equipment for use in explosion hazardous areas.	
	Flameproof enclosure (d)	EN 60079-1	In the case of ignition inside the encapsulation, the enclosure must withstand the pressure, and a transfer of the "inner" explosion to the outside must be ruled out.	1 2
₽¥¥ ¥ ¥ ₹	Presurised enclosure (p) (pD ²) (px) (py) (pz)	EN 60079-2 EN 61241-4	A protective gas, which is under overpressure, (min 0.5 mbar) encloses and separates the ignition source from the surrounding atmosphere.	2
*	Sand filling (q)	EN 60079-5	The finely grained material encloses the ignition source. An electric arc generated in the inside of the housing must not be capable of igniting the potentially explosive atmosphere during normal operation.	1 2
*	Oil immersion (o)	EN 60079-6	Protection type "oil immersion" implies that the electrical apparatus and its components are separated from the potentially explosive atmosphere by immersion in oil.	1 2
	Increased safety (e)	EN 60079-7	This protection type (e) applies only to electrical equipment and its components which is incapable of generating danger- ous sparks, electrical arcs or thermal effects during normal operation. The voltage rating of this type of equipment may not exceed 11 kV.	1 2
	Intrinsic safety (ia) (ib) (ic)	EN 60079-11	The energy in the current circuit is limited to such an extent that sparks, electrical arcs or high temperatures cannot be generated.	0 1 2
	Non sparking apparatus (nA)	EN 60079-15	Sparking is excluded. Clearances and creepage distances are determined. Maximum surface and component temperatures are limited. The protection degree of the housing has to be at least IP54/IP44. Area of application: zone 2.	2
{ <u> </u>	Sparking apparatus (nC) (nR)	EN 60079-15	The protection type applies to sparking equipment, in which contacts are appropriately protected by: - enclosed switching device - enclosed i.e. sealed equipment - hermetically sealed housing. Area of application: zone 2.	2
	Encapsulation (m) (ma) (mb) (mc)	EN 60079-18	Possible ignition sources are encapsulated in a potting material so that they are incapable of igniting an explosive atmosphere.	20 21 22
	Intrinsically safe electrical systems (ia) (ib) (ic)	EN 60079-25	Distinguished are: - certified intrinsically safe systems - certified intrinsically safe systems An intrinsically safe system is the approved assembly of interconnected electrical equipment (intrinsically safe and associ- ated apparatus). It is documented accordingly in the system description.	0 1 2
	Optical radiation (op pr) (op sh)	EN 60079-28	The optical radiated power is limited so that it is incapable of igniting an explosive atmosphere.	1 2
- ↓ + s	Protection by housing (t ^{2,}) (ta) (tb) (tc)	EN 60079-31	The enclosure is so dense that no combustible dust can enter it. The surface temperature of the outer enclosure is limited.	20 21 22

	d	evice's	s mar	king.
--	---	---------	-------	-------

Marking of an associated apparatus acc. to ATEX (for example):										
<	II	(1)	G					
symbol	all areas except mining (mining = I)	associated appartus	very high safety level suited for zone 0 (two independent means of pro- tection)	associated appartus	explosion pro- tected against gas, vapour and mist (D = dusts)					

Preconditions for an explosion



The cable characteristics provided by the manufacturer should be used. Should these not be available, it is recommended to apply the following typical values (acc. to EN 60079-14):

 $L_c = 1 \,\mu\text{H/m} (30 \,\mu\text{H/}\Omega)$

 $C_{c} = 200 \text{ pF/m}$

Connection of proximity switches to isolating switching amplifiers, or 2-wire transmitters to isolating transducers, or solenoid valves to a valve control module can be considered as simple circuits.

General guidelines for the use of devices with intrinsically safe circuits

It is required to observe a safety distance of 3 mm (EN 60079-11) to earthed components, such as covers or side panels of mounting cabinets. A thread measure of 50 mm must be observed between intrinsically safe connections and non-safe connections.



Ignition temperature and classification of combustible materials according to groups and temperature classes (I = mining areas susceptible to fire damp II = all other atmospheres)

450 °C	Maximum surface temperature of apparatus					
300 °C						
200 °C						
135 °C						
100 °C						
85 °C	T1	T2	T3	T4	T5	T6
1	Methane					
IIA	Aceton Ammonia Amyl Acetate Benzene Acetic Acid Ethane Ethyl acetate Carbon monoxide Methane Methanol Propane Toluene	Butane Butanol Ethanol	Benzines Diesel fuel Hexane			
IIB	Town gas	Ethylene	Hydrogen sulphide	Diethyl ether		
IIC	Hydrogen	Acetylene				Carbon disulphide

www.turck.com

Hans Turck GmbH & Co. KG Witzlebenstr. 7 45472 Muelheim an der Ruhr Germany Tel. +49 208 4952-0 Fax +49 208 4952-264 E-Mail more@turck.com D200457 2014/04_V1.2 Subject to change without notice • Edition 04.14 • © Hans Turck GmbH & Co. KG 2014